

ZBS-TAxx

Wall-Mount Switch and Dimmer

ZBS-TA01 is designed to effortlessly replace the existing wall-mount switches at home or in the office environment. It can be configured to turn on/off the load in conjunction with other Zigbee end-nodes, it is also a dimmer that can wirelessly dim your light output. It fits in existing wall switch wiring box with full range AC input from 110-277VAC. It works seamlessly with ZGW-C01 and ZGW-A01 or any other Zigbee Gateways that are Zigbee HA 1.2 compatible.

PRODUCT FEATURES

- Zigbee H.A 1.2 compatible; control lighting fixtures wirelessly.
- 4 Buttons touch pad the with LED back-light
- Fit with standard off-the-shelf switch covers
- Fit in standard wall switch junction box.
- 100VAC - 277VAC full range input for no-worry installation
- High interoperability in compliant to global Zigbee standards.
- Start of the are algorithms providing seamless smooth dimming effect.
- Easy commissioning, easy to use and easy to control
- Standard Zigbee OTA makes updating easy and current.

SPECIFICATIONS

COMPATIBILITY :	Zigbee H.A 1.2
INPUT :	110 – 277VAC/ 50-60Hz
OPERATING ENVIRONMENT :	-20 to +65°C
RADIO PROPERTIES :	2.4GHz, +19.5DbM Transmit Power
INTERNAL ANTENNA :	Built-In
EXTERNAL ANTENNA :	N/A
LED INDICATORS :	Solid(In network)
CONTROLS :	Flash (Paring Mode)
DIMENSIONS :	119 x 75.5 x 36mm (L x W x D)
WARRANTY :	5 Year

Project Name:	
Type:	



WARRANTY

- See [Limited Warranty Policy](#) for more additional information.

ORDER INSTRUCTIONS: *EXAMPLE: ZBS-TA02-12*

ZBS-	TA__ -	-
	01 Without load On/Off	04 4 Buttons; On/Off/ dim
ZBS	02 With Relay for On/Off control	08 8 Buttons; On/Off/ dim/ scenes
	03 With relay for TriAC dimming	12 12 Buttons; On/Off/ dim/ scenes